
- PAPER COPIES ARE UNCONTROLLED -

All ecoPhos® H2 LED MR16 will work with iron core transformers and DC drivers. Our tests indicate that H2 MR16 are compatible with most electronic transformers.

COMPATIBLE ELECTRONIC TRANSFORMERS:

1. CLIPSAL CDL1E60 (1 or 2 MR16's)
2. CROMPTON Lightstar white & blue LS60 (25242) (1 or 2 or 3 or 4 MR16's)
3. CROMPTON red EXEL 60VA (1 or 2 or 3 or 4 or 5 MR16's)
4. DOMUS Halo LTH60 (16784) (1 MR16)
5. EXPO Model CRC60 code 25059 (grey & orange) (1 or 2 MR16's)
6. GALAXY Model GALCOBRA (black) (1 or 2 or 3 or 4 or 5 MR16's)
7. GALAXY Model GALTRF_REXFP (white & green) (1 or 2 MR16's)
8. LUXMAN ETH 60.2 (1 or 2 or 3 or 4 MR16's)
9. LUXMAN ETH60.202 (1 or 2 or 3 MR16's)
10. LUXMAN ETH70 20-70W (1 or 2 or 3 or 4 or 5 MR16's)
11. NELSON MICRO60 (1 or 2 or 3 MR16's)
12. NELSON MTECOUGAR60 (1 or 2 or 3 or 4 or 5 MR16's)
13. NELSON MTETRADE65 "The Tradesman" (1 or 2 MR16's)
14. OSRAM ET-Redback 60VA/230-240 (1 or 2 or 3 or 4 or 5 MR16's)
15. OSRAM Halotronic HTM 105/230-240 (1 or 2 or 3 or 4 or 5 MR16's)
16. PIERLITE GD-32 (1 MR16)
17. R & C green UNA2005 (1 MR16)
18. SUNNY grey and white MINI –TP713B (1 or 2 or 3 MR16's)
19. TRADEFORCE TRFELT60T (1 MR16)

INCOMPATIBLE ELECTRONIC TRANSFORMERS

1. ACTEC Series II MINI60
2. ALLUME TX-AL60
3. CROMPTON CROTR19TBK
4. LUXMAN ETH105.4 35-105VA
5. LUXMAN ETH50.3 IP67
6. NELSON Kitty 105
7. PIERLITE Black LSI-61
8. TRIDOINC Atco Possum
9. TRIDONIC Atco Viper

DIMMING

The ecoPhos® H2 LED MR16 is dimmable with a Clipsal universal dimmer and iron core transformer. Up to 6 LEDs can be used on generic 50 watt transformer; more LEDs can only be used with larger transformers.

MORE INFORMATION

Refer to our website for updates at www.ecobright.com.au or call your nearest ecoBright® office.

<<< End of Document >>>

- PAPER COPIES ARE UNCONTROLLED -
